

SAW Resonator

TO-39 Series SAW Resonator

303MHz~868MHz

Size: 9.5×9.5×3.5mm



Features

- 1-port resonator, Metal can 9.5×9.5×3.5mm 3-pin package
- Package code: TO-39
- Low insertion loss
- Electrostatic Sensitive Device (ESD)
- Frequency range: 303MHz~868MHz
- Applications: Alarm, Remote control, PEPS, Automotive electronics, Consumer electronics, etc
- RoHS Compliant /Pb Free



Standard Specifications

Part Number	Center Frequency (MHz)	Frequency Tolerance	Insertion Loss (dB) max.	Package Code
R303.825	303.825	±30KHz/±75KHz	1.5	TO-39
R303.875	303.875	±30KHz/±75KHz	1.5	TO-39
R310	310	±30KHz/±75KHz	1.5	TO-39
R315	315	±30KHz/±75KHz	1.5	TO-39
R316.8	316.8	±30KHz/±75KHz	1.3	TO-39
R330	330	±30KHz/±75KHz	1.6	TO-39
R350	350	±30KHz/±75KHz	1.5	TO-39
R360	360	±30KHz/±75KHz	1.4	TO-39
R370	370	±30KHz/±75KHz	1.7	TO-39
R390	390	±30KHz/±75KHz	1.5	TO-39
R407.3	407.3	±30KHz/±75KHz	1.4	TO-39
R418	418	±30KHz/±75KHz	1.6	TO-39
R433	433.92	±30KHz/±75KHz	1.9	TO-39
R868	868.35	±75KHz/±150KHz	2.1	TO-39

Note: More frequencies, more information, please contact with our sales department directly.

Dimensions

Pin No.	Function
1	Input /Output
2	Output /Input
3	GND